www.sylvania.com



LED MR16







Applications

Accent / display lighting **Ambient lighting** Art galleries Decorative room lighting High-end retail Highlight heat-sensitive merchandise Highlight merchandise Hotels Restaurants

The compact SYLVANIA LED MR16 is designed to fit into standard MR16 low voltage fixtures and sockets. It is ideal for use with tracks, rails, cables and pendants in interior architectural, retail, exhibit, display, and residential applications.

The lamp features standard MR16 bi-pin connectors and a sleek housing with chrome finish. LED MR16 comes in blue or white (white available in 3000 and 3500 Kelvin). Unlike conventional light sources that decrease in color temperature as they are dimmed, the MR16 will maintain a constant color temperature.





Ordering Information

Product Order Code*	Catalog Description	Inner SKUS of the Counter Display unit	Wattage (W)	Voltage (V)	mA	Max. Luminous Intensity (cd)	Luminous Flux Φ (lm)	Beam Angle (degree)	Base	LED Color	Luminous Life (hrs)
72084	LED/MR16/DRAGON/W/ 730/NSP6/COUNTER	72095	2.8	12	500	869	24	6	GU5.3	3000K	15,000
72085	LED/MR16/DRAGON/W/ 735/NSP6/COUNTER	72096	2.8	12	500	955	27	6	GU5.3	3500K	15,000
72086	LED/MR16/DRAGON/B/ NSP6/COUNTER	72097	2.8	12	500	303	9	6	GU5.3	Blue (470nm)	15,000

*for reordering please reference the product order code

OSRAM SYLVANIA National Customer Service and Sales Center 18725 N. Union Street Westfield, IN 46074

Consumer Products

Phone: 1-800-842-7010 Fax: 1-800-842-7011

Industrial Commercial

Phone: 1-800-255-5042 Fax: 1-800-255-5043

National Accounts

Phone: 1-800-562-4671 Fax: 1-800-562-4674

OEM/Specialty Markets

Phone: 1-800-762-7191 Fax: 1-800-762-7192

Display/Optic

Phone: 1-888-677-2627 Fax: 1-800-762-7192

In Canada OSRAM SYLVANIA LTD. Headquarters 2001 Drew Road Mississauga, ON L5S 1S4

Industrial Commercial

Phone: 1-800-263-2852 Fax: 1-800-667-6772

Special Markets

Phone: 1-800-265-2852 Fax: 1-800-667-6772

1-800-LIGHTBULB

Visit our website: www.sylvania.com

Application Information

CAUTIONS

- To avoid electrical shock and early lamp failure, this lamp must only be used indoors and in dry locations
- No user serviceable parts inside. To avoid electrical shock, do not disassemble lamp
- This lamp is not intended for use in emergency light fixtures or exit signs
- LED MR16 lamps will not dim. The lamps will extinguish at lower dimmer settings. Dimming circuits will not harm the lamps
- LED MR fits most standard, low voltage MR16 lighting fixtures including: track, strips for case lighting, adjustable downlighting, landscape lighting and recessed lighting
- LED MR16 lamps are not compatible with integral electronic transformers; LED MR16 lamps can run on magnetic transformers only

Dimensions





